

VerteX[®]

NEUTRAL PH 7 CONDENSER & EVAPORATOR CLEANER



Ready to use



Aerosol



Concentrate



Condensate pump safe

KEY FEATURES

- Non corrosive - neutral pH 7 adaptive cleaner
- Quickly removes rust, scale, grease and fat
- Ideal for microchannel and coils with protective coatings
- Neutralises all unpleasant malodour
- Makes 25-45 litres*

Part No.	Product	Qty	Size
S010389GB	VerteX	4	5L

*1:8 - Evaporators. 1:4 - Condensers.



EnviroCoil[®]

UNIVERSAL COIL CLEANER



Ready to use



Aerosol



Concentrate



Condensate pump safe

KEY FEATURES

- Biodegradable, environmentally friendly and mild formulation
- Perfect for most maintenance, indoors or outdoors
- Contains no acids, phosphates, sodium/potassium hydroxide
- 5L: Makes 25-45 litres / 20L: Makes 100-180 litres*

Part No.	Product	Qty	Size
S010167GB	EnviroCoil	4	5L
S010312GB	EnviroCoil	1	20L

*1:8 - Evaporators. 1:4 - Condensers.



EasyClean[®]

UNIVERSAL COIL CLEANER



Ready to use



Aerosol



Concentrate



Condensate pump safe

KEY FEATURES

- Suitable for use on both air cooled evaporators and condensers
- Convenient, high powered aerosol with a safe formulation
- Attacks only the dirt, not the coil

Part No.	Product	Qty	Size
S010128GB	EasyClean	12	600ml

Hazardous transport.



Technical data sheet

EasyClean®

Universal coil cleaner



EasyClean® is an effective cleaner, suitable for use on both evaporator and air cooled condenser coils. Its formulation is safe to use, making it perfect for regular maintenance.


PRODUCT SPECIFICATION

Name	EasyClean®
Product Code	S010128GB
Packing Quantity (ml, L)	12 x 600ml
Packing Size (L x H x D cm)	21 x 29 x 27
Shipping Weight (kg)	7.48
Shipping Volume (m³)	0.0164
Soils	Grease and dirt deposits


Special Features

- Dual purpose

Directions of use




1. CHECK POWER



2. SPRAY



As required



4. RINSE

Evaporators: fan may be kept running, depending on system configuration.

Condensers: turn system off. Isolate electrics.

If working in a confined area, ensure sufficient ventilation. Start cleaning at top, holding aerosol close to coil face. Work methodically, moving across the coil and then down. Ensure the coil is completely saturated. If necessary, place card or cloths behind the coil to catch loosened dirt. Repeated applications may be required for very dirty coils. Rinse thoroughly with fresh water.



EasyClean®
UN1950
Warning
Contains Propan-2-ol

H223: Flammable aerosol. H229: Pressurised container: May burst if heated H319: Causes serious eye irritation. P210: Keep away from heat, hot surfaces, sparks, open flames and other ignition sources. No smoking. P211: Do not spray on an open flame or other ignition source. P251: Do not pierce or burn, even after use. P280: Wear protective gloves / protective clothing / eye protection / face protection. P305+351+338: IF IN EYES: Rinse cautiously with water for several minutes. Remove contact lenses, if present and easy to do. Continue rinsing. P410+412: Protect from sunlight. Do not expose to temperatures exceeding 50 °C.

Caution: Pressurised container. Protect from sunlight and do not expose to temperatures exceeding 50 °C.

Do not pierce or burn even after use. Do not spray onto a naked flame or any incandescent material.

Restricted to professional users.